

Touch Dimmer TD001

Description	Dimension	Voltage	Load
Touch Dimmer	10mm x 43mm	12-24VDC	Max. 8 Amps.



V+ ----DC input positive

V- ----DC input negative

DC input parameters

Input Voltage 12V-24V DC Maximum.

Input Current Maximum 8A

LED+ --- Output to LED Strip positive

LED- --- Output to LED Strip negative

The conductive spring needs to be covered by insulation material such as glass, plastic or ceramic material.

● 4 Steps Dimmer

Off → supper low → low → medium → high → Off....

Touch Times	Brightness	Percentage of full load
0	Off	0%
1	Super Low	6%
2	Low	28%
3	Medium	60%
4	High	99%



Note: The function/program can be customized made upon different needs, such us- with/without memory, longer time for stay on, etc.....

Lister: Lxlan

Assessor: 

Approver: 